

NEBULA PIR



Automatically turns lights on when movement is detected



5 minute PIR sensor/switch



Choice of lighting levels



Robust construction with unique impact deflection design



Quick and easy to install



E-type approved













DESIGNED FOR MULTI-SECTOR APPLICATIONS












NEBULA PIR

Built in PIR sensor/switch - The electronics used within the PIR sensor/switch have been designed to detect the movement of body heat to activate the sensor. Once the sensor has been triggered, the unit will switch on for the specified time before automatically switching off, preventing any unnecessary load, thereby extending battery life. If continuous movement is detected then the lights in the vehicle will remain on. This not only saves on battery power but there are also cost savings to be made on installation as a separate switching device is not required.

Long life, high intensity Cree LEDs - The Nebula PIR incorporates the Orizon LED strip light which uses the latest in Cree LED technology, offering optimum performance and extended life. This unit is available with a choice of light output and lengths to suit a wide variety of applications and budgets.

Quick and easy to install - The Nebula PIR is simply fixed into place by the end caps, making it suitable for both new vehicle specifications and retrofitting into existing vehicles.







SPECIFICATION ALL DIMENSIONS HAVE A TOLERANCE OF +/-1mm				
	12VDC	SI5CW250PIR (12 LED - 12V)	SI5CW500PIR (24 LED - 12V)	
Voltage Range Average Current Light Output Watts Weight Temp. Range IP Rating (switched)* IP Rating (non switched)*	VDC A Im W kg °C IP	10-14 0.24 320 3W 0.08 -30 to +40 IP60	10-14 0.44 640 6W 0.38 -30 to +40 IP60 IP60	The PIR version is not currently available with 48 LEDs in 12V
	24VDC	SI5CW250/2PIR (12 LED - 24V)	SI5CW500PIR (24 LED - 24V)	SI5CW1000/2PIR (48 LED - 24V)
Voltage Range Average Current Light Output Watts Weight Temp. Range IP Rating (switched)* IP Rating (non switched)*	VDC A Im W kg ℃ IP IP	20-28 0.12 320 3W 0.08 -30 to +40 IP60	20-28 0.22 640 6W 0.38 -30 to +40 IP60	20-28 0.5 1280 12W 0.7 -30 to +40 IP60 IP60

E & OE | Calculations based on average LED values @ 13.2V (for 12V models) and @ 26V (for 24V)



^{*} LED strip = IP66